

## 15 Watt LED Fixture

The IHT Lighting 15-watt high efficiency LED fixture is designed to provide optimal illumination of agricultural, commercial and industrial facilities. The fixture is designed to provide reliable and consistent performance in a wide variety of lighting applications.

### Features

- Suitable for wet/damp locations (4X/IP66)
- 150-degree beam spread with new re-designed optical lens
- Driver provides consistent output over varying voltage conditions
- Ring Wave Surge Tested to 2,500 volts
- Lightweight, impact resistant, anti-corrosive enclosure/ lens
- Energy efficient - Designed to replace 100W incandescent or 25 watt CFL
- Adapter compatibility with most jelly jar junction boxes (Easy installation with E26 socket connector accessory)
- Low maintenance
- Low operating temperature - Internal aluminum heat sink

### Specifications

<b>Power &amp; Lumen output</b>	15 watt/2100lm (140lm per watt)
<b>Dimensions</b>	4.09 x 4.70 inches (10.4 x 11.9cm)
<b>Color temperature CCT</b>	5,000K (Day White)
<b>Color rendering index</b>	80
<b>Rated life (L80)</b>	5 Years (DOP) / 50,000 Hours
<b>Beam spread</b>	150° Degree
<b>Operating temperature</b>	-20°C to +45°C (-4°F to 113°F)
<b>Input voltage</b>	100 - 277V/AC 50/60hz
<b>Dimmer type</b>	Non - Dimmable
<b>Power factor</b>	>0.9
<b>Environment</b>	Rated for wet and damp locations (IP-66/4X)



### Applications

- Agriculture
- Commercial / Industrial
- Tunnels / Corridors
- Warehousing

# Available Configurations

---

## JELLY JAR MOUNT

Best for outfitting rooms with existing Jelly Jar Lights

- ✓ 15W LED Fixture
- ✓ E26 Adapter



## JUNCTION BOX MOUNT

Best for outfitting rooms with existing PVC Junction Boxes

- ✓ 15W LED Fixture
- ✓ Hardwire Adapter
- ✓ Rubber Gasket
- ✓ Junction Box adapter with mounting screws



## FULL MOUNTING KIT

Best for new construction

- ✓ 15W LED Fixture
- ✓ Hardwire Adapter
- ✓ Rubber Gasket
- ✓ Wiring Compartment adapter with mounting screws
- ✓ Wiring Compartment

